naturaled®

HID RETROFIT (CCT3)

DESCRIPTION

naturaLED[®] High Quality LED Retrofit Kits have been designed specifically for your existing HID fixtures. Delivering up to 2X higher lumens and efficacy compared to retrofits using generic LED kit. Utilizing high-efficiency LEDs and reliable drivers will save you time, energy, and money! Mounting options and adjustability for Indoor and Outdoor applications to fit various fixture types. Available in 3 Color Selectable or CCT in 5000K. Wide and even light distribution is a perfect replacement to use for existing fixtures: Shoebox, High Bay, Low Bay, Flood, Wall Pack and much more. Easy replacements for existing metal halide HID, high-pressure sodium, or mercury vapor light bulbs and ballasts.

APPLICATIONS

Warehouse, Security, Pathway, Street, Area Lighting

FEATURES

- DLC Premium Qualified
- ETL Listed
- ColorTemp: 3CCT (3000K,4000K,5000K), 5000K
- •Voltage: 120-277V
- Power Factor: >0.9
- Surge Protection: 4KV
- Beam Angle: 120°
- Dimmable: 0-10V
- CRI: >80
- Operating temperature: 40°F 140°F
- Retrofit any high/low bay, wall pack, flood light & area light
- Yoke mount included with adjustable positoin
- Color: Black
- 5 Year Warranty
- Optional Accessories for Purchase: Adapter, Surge Protector, 277-480V Drivers

SAMPLE NUMBER RKIT50HID/8CCT3					
SERIES	WATTAGE	REPLACEMENT	CRI	COLOR TEMP	
RKIT	50	HID	8	CCT3	
Retrofit Kit	50 Watt	Metal Halide HID	CRI 80	Color Temperature (3000K/4000K/5000K)	



© 2024 naturaLED® All rights reserved www.naturaLED.com Toll-Free: 855.758.7009 PROJECT:

DATE:

SCHEDULE: PREPARE BY:

NOTES:



ACCESSORIES



HID RETROFIT (CCT3) wall & area luminaires

*P= Premium DLC / *S = Standard DLC


Watts (W)	Ordering Code	Description	ССТ (К)	Lumens (Lm)	Equiv. Wattage (W)	Size	Dim (V)	DLC (S/P)
50	9600	RKIT50HID/8CCT3	3CCT (3/4/5K)	6,367	250-400	3.0″x4.80″	0-10V	Р
100	9601	RKIT100HID/8CCT3	3CCT (3/4/5K)	12,978	400	3.0"x4.80"	0-10V	Р
180	9602	RKIT180HID/850	5000K	24,496	400-575	5.79″x4.80″	0-10V	Р
240	9603	RKIT240HID/850	5000K	32,170	750-1000	5.79″x4.80″	0-10V	Р

ACCESSORIES (Ordered Separately)


ORDERING

Base		Driver
	P10374 MT-RKIT-E26 (Mount E26 Adapter for HID Retrofit)	Driver (Included with HID Retrofit)
	E39 Socket (INCLUDED) (Included with HID Retrofit)	
Surge Protect	or	Driver (277-480V)
Surge Protect	or P10389 SPD-L-10KV-277 (Surge Protection 10KV 120-277V)	Driver (277-480V) P10448 BALED-SS-100M-56BH (277-480V Driver for RKIT100W #9601)


DIMENSIONS



PHOTOMETRICS CHART



PACKAGE



© 2024 naturaLED® All rights reserved www.naturaLED.com Toll-Free: 855.758.7009